



Phono BOX MM

Phono preamplifier

- Suitable for MM cartridges (Moving Magnet)
- Precise RIAA equalisation
- Dual mono circuitry for optimized channel separation
- Low noise ICs
- Gold-plated RCA in & outputs
- Metal casing protects from vibrations and electromagnetic interference
- Black lacquer finish

Input impedance: 47kohms

Capacitance: 120pF

Gain MM: 40 dB

Output voltage: 500mV @ 1kHz
(with 5mV input voltage @ 1kHz)

Noise floor: - 88dB

THD: < 0,04%

RIAA equalisation curve accuracy: within
0,5dB/20Hz - 20kHz

Input: RCA

Output: RCA

Power supply: 18V/500mA DC; 220 - 240V, 50Hz

Power consumption: 20 mA DC, < 1 watt standby

Dimensions W x H x D: 107 x 30 x 75 mm

Weight: 280g without power supply

Phono preamplifier for MM cartridges

Today, many amplifiers do not have a specific phono cartridge input. Phono Box MM is an ideal phono preamplifier for these hifi systems. Phono Box MM accepts MM cartridges and offers an audiophile music experience at an entry-level price. Advanced circuitry keeps noise and distortion at a surprisingly low level. The metal case shielding and an outboard DC power

supply leave no risk for external interference. Because of its small casing, Phono Box MM can be placed near the turntable. Input and output sockets are gold-plated for preservation of quality. Phono Box MM can be connected easily to a line-input (AUX etc) of your amplifier.

